

ETC Release Note

Eos® Family Lighting Control Software

Product Line:	Eos Family Lighting Control
Description:	Version 2.5.2 System Software
Engineering Change Master (ECM):	500016925
Effective Date:	2017-04-04

Purpose

The primary purpose of this release is to address a lockup when using a networked RFR. There are a small number of other issues also addressed in this release. It is recommended that users update to this release as soon as their production schedules allow.

This software release is highly recommended for all users of the Eos Family platform (Eos Ti®, Eos®, Gio®, Gio @ 5™, Ion®, Element™, ETCnomad®, and ETCnomad Puck®).

For any questions relating to the contents of this release or the behavior of this software, please contact ETC Technical Services at the office nearest you. A list of ETC offices is given at the bottom of this page.

Availability

You may obtain this release of software by downloading it from the Downloads section of the ETC website, www.etconnect.com.

Documentation

The current documentation for Eos Titanium, Eos, and Gio is the Eos Family v2.5.1 Supplement to Operations Manual Revision A, and the Eos Titanium, Eos, and Gio v2.0 Operations Manual Revision A. The current documentation for Ion is the Eos Family v2.5.1. Supplement to Operations Manual Revision A, and the Ion v2.0 Operations Manual Revision A. The current documentation for Element is the Eos Family v2.5.1 Supplement to Operations Manual Revision A. and the Element v2.1 User Manual Revision A.

Please keep this release note with your user manual for descriptions of the newest features, changes and bug fixes in Eos.

ETC manuals can be downloaded free of charge from ETC's website at www.etconnect.com. They are available in portable document format (pdf), and viewable with Adobe® Acrobat® Reader™ v8.x and later.

Affected Products of This Release

The following Eos Family products are affected by this software release:

- Eos Titanium
- Eos
- Gio
- Gio @ 5
- Ion
- Element
- Eos Remote Processor Unit (RPU)
- Eos Remote Processor Unit 3 (RPU3)
- Ion Remote Processor Unit (RPU)
- Net3 Remote Video Interface (RVI)



Corporate Headquarters ■ Middleton, WI, USA ■ Tel +608 831 4116 ■ Service: (Americas) service@etconnect.com

London, UK ■ Tel +44 (0)20 8896 1000 ■ Service: (UK) service@etceurope.com

Rome, IT ■ Tel +39 (06) 32 111 683 ■ Service: (UK) service@etceurope.com

Holzkirchen, DE ■ Tel +49 (80 24) 47 00-0 ■ Service: (DE) techserv-hoki@etconnect.com

Hong Kong ■ Tel +852 2799 1220 ■ Service: (Asia) service@etcasia.com

Web: etconnect.com ■ © 2017 Electronic Theatre Controls, Inc.

Product information and specifications subject to change. ETC intends this document to be provided in its entirety.

4250M1100-2.5.2 ■ Rev A ■ Released 2017-04

ETC Release Note

Eos Family Software v2.5.2

- Net3 Remote Video Interface 3(RV13)
- ETCnomad (PC & Mac Client/Offline)
- ETCnomad Puck

Key Enhancements in v2.5.2

- Bug Fixes

Key Enhancements in v2.5.1

- Bug Fixes
- Fader Unmap on Delete Option
- Clear Filter Controls in Fader Configuration
- Syntax Modifications.

Issues Corrected in v2.5.2

- RND 0040789 Gio @5 Effects Editor has Parameter Icons Cut Off
- RND 0040784 [chan 1 make Null] with a range of cues selected, can create an illegal move
- RND 0040720 Custom Gel Scrolls and Gobo Wheels Are Lost During an Undo
- RND 0040707 When the last cue is auto-fired, persistent storage restores the previous cue.
- RND 0040615 Random lockup using network RFR
- RND 0040576 Snapshots: DS: Firing a DS Bank in Expand Causes a 15 to 35 second lockup
- RND 0040342 Add high DPI support to Eos to support 4K/QHD and other high-resolution formats
- RND 0039229 You can no longer double click consistently in Eos

Known Issues Remaining in v2.5.2

- RND 0040729 [chan 1 recall from recall from] should post [cue]
- RND 0040684 Tab 36: All exclude flags on subs are shown as Ex:Record
- RND 0039561 Discrete Time 't' missing in collapsed Live Channel display
- RND 0038513 Multiple Query conditions acting as OR instead of AND
- RND 0037797 Magic Sheets - Command item ignores the plus character in macro mode
- RND 0037690 PDF - some text can be cut off in printouts using different languages
- RND 0037364 OSC - /eos/key/go is no longer firing cues.
Workaround: Use /eos/key/Go 0 or /eos/key/Go_0
- RND 0037164 Selection Bounces in Fixture Editor Table when Scrolling Off of the Right Side
- RND 0035098 ASCII Import: must prevent multiple channels patched to one Address
Workaround: Save the to a .esf file and re-load this .esf file. This cleans up the bad condition.
- RND 0032709 Encoder_Category_button page number is not macroable
- RND 0030257 Captured channels manual effects not recording into existing sub
- RND 0029871 When editing a scroll, the blank space to the right of the scroll bar can select a gel
- RND 0029865 Macro editor display is empty if it is displayed in too small of a window
Workaround: For both cases, closing the CIA works as expected.
- RND 0029823 2 pixmaps with the same server channel can output incorrectly.
- RND 0029769 Custom fixture editor giving error when editing mode ranges
- RND 0029752 Rate overrides less than 10 running too slow
- RND 0029708 Print to file will crash if there isn't enough space available
- RND 0029193 [Magic Sheet 1 Copy To Magic Sheet] resets the command line, [Magic sheet 1 CopyTo 2] does not
- RND 0029155 Macro that turns on/off the internal SMPTE clock doesn't work in the show control display.
Workaround: Set the macro mode to Background.
- RND 0027991 Undo selection does not properly track to different devices of the same user.
- RND 0027983 Undoing manual values snap to previous level instead of using Manual time in setup
- RND 0027372 After using [Record Rig Check] Eos reports 'Not Recorded' – CEM3 reports that it has been recorded.

ETC Release Note

Eos Family Software v2.5.2

Known Issues Remaining in v2.5.2 [Continued]

- RND 0027148 [Shift + Escape] to lock desk can't be learned into a macro
- RND 0027099 Physical Direct Select Displays are not removed when Eos is started without physical direct selects
- RND 0027034 Reset this Workspace or Reset All Monitors and Workspaces should reset tabs 1 and 2 to Eos defaults
- RND 0027004 USB RFR does not work if you restart Eos on Windows 8.1
- RND 0026147 When shutter strobe is marking, intensity outputs nonzero value output strobe
- Workaround:** The user can either Disable automark on that cue, or put the shutter mode change in a follow cue.
- RND 0016827 Snap Intensity Params are fading on timed HTP sub bump
- RND 0011875 Eos Client - Windows 7 compatibility issues
- RND 0011798 Build Step effect with Stop/Hold exit, stops at off states, not on states
- RND 0011779 Rem Dim does not override intensities coming from Intensity Effects.

Compatibility

ACN

The software is compatible with all Net3™ products that meet or exceed ESTA ratified standard ANSI E1.17 2006 Architecture for Control Networks (ACN) and ANSI E1.31 Streaming ACN (sACN).

ETCNet2 Network Compatibility

This release is compatible for the exchange of EDMX and/or configuration information with the following ETC hardware and software:



CAUTION: *Eos ETCnomad (Mac and PC) and Puck do not support ETCNet2 protocol. See the [Incompatibility](#) section.*


- Eos® Family Lighting Control System - Version 1.0.0 and later software.
- Congo™ Family Lighting Control System - Version 4.0.0 and later software.
- Emphasis® Control System - Version 1.4.0 and later software.
- Obsession® II Control System - Version 5.1.x software.
- Network Configuration Editor (NCE) - Version 4.x.x and later software.
- Net3 Four Port Gateway (ETCNet2 mode) - Version 4.0.0 and later software.
- ETCNet2 DMX Node - Version 4.0.6 and later software.
- ETCNet2 Two Port Node - Version 4.1.4 and later software.
- Unison® - Version 1.9.x software.

ETC Release Note

Eos Family Software v2.5.2

Incompatibility

Eos v2.5.2 is incompatible with hardware and software running ETCNet2 software prior to those listed above.

 **CAUTION:** *Until your ETCNet2 nodes and Net3 gateways running in Net2 mode are updated to the versions listed below by NCE v4.2 or later, you must turn off/disable the (DHCP) Address Server in the Eos Configuration Utility (ECU). In the ECU: Settings>Network>Net3 Settings. Make sure "Enable Address Server" is unchecked.*

Software Versions that are compatible with DHCP servers:

ETCNet2 DMX Node (4.0.6)

ETCNet2 Two Port Node (v4.1.4)

ETCNet2 Video Node (v4.0.2)

Net3 Four Port Gateway (ETCNet2 mode v4.0.3 or later)

Eos v2.5.2 is incompatible with hardware and software running ETCNet1.

Eos ETCnomad (Mac and PC) and Puck are incompatible with hardware and software running ETCNet2 protocol.

Installation Instructions

For new Eos Family consoles, ETC has implemented a method to include the latest software installers directly on the console's hard drive when they initially ship from ETC. For future releases, you will need to download the Eos Family software from the ETC website, www.etconnect.com.

 **Note:** *All processors on the Eos Family network must be running the same version of software. Therefore, you must also update all RVIs and RPUs when you update your console.*

Installer Archive

To check to see if a newer version of Eos software is available on your console, navigate to **ECU>Settings>General>Software Update**.

When the software update window launches, it will show you the available Eos versions found.

If there is an available update and you wish to install it, follow the on screen steps for updating the console's software.

The Installer Archive can also be used to save multiple software versions onto your console's hard drive in case you wish to downgrade.

Software Installation

To update your console or offline software to the v2.5.2 release, you will need to download it from the ETC website, unzip the file, load it to a USB device, and then transfer it to your console from the USB port using the Eos Configuration Utility (a.k.a. Eos Shell).

To update your console to v2.5.2:

- 1: Download the software from the ETC website (www.etconnect.com - click "Downloads" at the top of the page).
- 2: Unzip the file.
- 3: Transfer the unzipped file to a USB memory device.
- 4: Insert the USB device containing the software into an available USB port on the console.

ETC Release Note

Eos Family Software v2.5.2

- 5: Open the Eos Configuration Utility (ECU - Also known as the Eos Shell) either by exiting the Eos Family software (**Browser>Exit**) or by starting up the console and clicking on the **{Launching in...}** button. The ECU screen will open.
- 6: Click on the **{Settings}** button. The settings window will open.
- 7: Click on the **{General}** button inside of the settings window. The general settings will appear in the window.
- 8: Scroll down in the window until the **{Software Update...}** button is visible. Click this button.
- 9: This scans the root directory of all available drives (USB drives) for valid installers.
- 10: When the "Update Software" dialog pops up, click on **ETC_EosFamily_Console_v2.5.2.9.0.8**, then click **{Install}**.
- 11: The software will copy to the hard drive before launching a standard Installshield application to direct you through the install.
- 12: Click **{Next}** to start the installation process.
- 13: Read and accept the terms of the license agreement and click **{Next}**.
- 14: A dialog box will open warning of losing show data if not saved to disk. Click **{Yes}** to continue. The console will install the software.
- 15: Click **{Finish}** to complete the installation process. The console will automatically reboot and then enter the ECU welcome screen.

ETCnomad (Client/Offline) Software

For system requirements and installation instructions for Windows and Mac clients, please see the ETCnomad Setup Guide.

Firmware Updates

The following table shows the current firmware versions. For information on updating firmware, please see the ECU appendix of your console's manual.



Note: *A restart of the console is required for every module updated.*



Note: *Single DMX port Gadgets and devices with IO cards that have a Phone Remote connection must use the **{Upgrade I/O Firmware}** button in the Maintenance tab of the ECU. Other IO cards and Gadget II can be updated using the firmware update window.*

ETC Release Note

Eos Family Software v2.5.2

Desk	Module	Current Firmware Version	Desk	Module	Current Firmware Version
Element			Ion RPU		
	Element Face Panel Board Firmware	1.1.90.Build 6 XPE / 1.2.90Build 7 for WES7*.		Eos RPU Front Panel	1.0
	FS I/O Board Firmware	1.4.2.9.0.5		FS I/O Board Firmware	1.4.2.9.0.5
	HS I/O Board Firmware	1.1.0.9.0.4		HS I/O Board Firmware	1.1.0.9.0.4
Eos			RPU3		
	Eos 1x5 Button Module	1.3		Ti 10x2 RPU Button Board Firmware	1.1.0.9.0.1 (1.1.9.1)
	Eos Encoder Rev A:	1.7		FS I/O Board Firmware	1.4.2.9.0.5
	Eos Keyboard Rev C:	1.1		HS I/O Board Firmware	1.1.0.9.0.4
	100mm Motorized Fader Rev D:	1.4 (or) 2.0	RV13		
Eos RPU				Ti 10x2 RPU Button Board Firmware	1.1.0.9.0.1 (1.1.9.1)
	Eos RPU Front Panel	1.0	Ti		
Gio				Fader Board Firmware	1.1.0.9.0.3(1.1.9 build 3)
	Gio Fader Board Firmware	1.1.0.9.0.3(1.1.9 build 3)		Face Panel Board Firmware	1.2.0.9.0.0(1.2.9 build 0)
	Gio Face Panel Board Firmware	1.2.0.9.0.0(1.2.9 build 0)		6x2 Button Board Firmware	1.1.0.9.0.1(1.1.9 build 1)
	Gio 6x2 Button Board Firmware	1.1.0.9.0.1(1.1.9 build 1)		Ti 6x1 Button Board Firmware	1.1.0.9.0.1(1.1.9 build 1)
	FS I/O Board Firmware	1.4.2.9.0.5		FS I/O Board Firmware	1.4.2.9.0.5
	HS I/O Board Firmware	1.1.0.9.0.4		HS I/O Board Firmware	1.1.0.9.0.4
Ion			Eos Programming Wing		
	Ion Face Panel Revision F:	1.3		Eos Playback Firmware	1.0.1.9.0.6
	FS I/O Board Firmware	1.4.2.9.0.5		Face Panel Board Firmware	1.2.0.9.0.0(1.2.9 build 0)
	HS I/O Board Firmware	1.1.0.9.0.4		HS I/O Board Firmware	1.1.0.9.0.4

ETC Release Note

Eos Family Software v2.5.2

Eos Motor Fader Wing 10/20			Gio @ 5		
	Display HS Universal Firmware	1.0.4.9.0.21		Eos Fader Wing Firmware	1.0.4.9.0.21
RVI				Gio @5 Motor Fader Firmware	1.0.0.9.0.4
	Eos RPU Front Panel	1.0		Intelligent Power Board Firmware	1.0.0.9.0.4
				HS 6x2 Button Board Firmware	1.0.0.9.0.4
				HS Face Panel Board Firmware	1.0.0.9.0.4
				HS I/O Board Firmware	1.1.0.9.0.4



Note: **For Elements that have Windows 7 installed but do not have firmware v1.2.90 or higher, please contact ETC Technical Services.*

Local RDM Firmware Update

New firmware is required for expanded functionality.

- Gadget -1.4.2.9.0.5
- IO Card -1.4.2.9.0.5

The new firmware is required for the use of Local RDM on any platform, and required for individual configuration of multiple IO devices on any platform.

Firmware can be updated from a console or PCs running Win7/8.1. Mac OS does not currently support firmware updates.

Dual NIC Update

This feature allows the console to be connected to two separate networks. Dual NIC is available on Eos Ti, Gio, and RPU3. For the second NIC to work fully, you must also install the ETC GCE Net3Svc v3.1 or higher. GCE is available for download from the ETC website (www.etcconnect.com - click "Downloads" at the top of the page). The new hardware for Ion, Element, Net3 RVI, and Ion RPU also include the dual NIC feature, but ship with GCE already installed.

Example applications:

- Support 2 separate Net3 Gateways, networks or sACN devices
- Support 2 separate networks (e.g., one sACN, one Artnet, or one sACN and one Network Attached Server)
- One network for 'output' devices (sACN, EDMX, Artnet...) and one network for controls an interfaces (Consoles, RPUs, Show control)
- One combined network and one limited traffic for wireless devices



Note: *The two Ethernet ports must be configured to separate networks (subnets). For proper operation, the two ports must NOT be connected to the same physical network.*

ETC Release Note

Eos Family Software v2.5.2

To enable the second network port

To configure the second Ethernet port on your console to match factory defaults, follow the instructions below. Otherwise, you may configure the second port to match your system requirements.

- 1: Open the Eos Configuration Utility (ECU - Also known as the Eos Shell) either by exiting the Eos Family software (**Browser>Exit**) or by starting up the console and clicking on the **{Launching in...}** button. The ECU screen will open.
- 2: Click on the **{Network}** button. The network window will open.
- 3: Set the IP address for port 2.
- 4: IP Address - 192.168.xxx.101
- 5: Subnet Mask - 255.255.0.0
- 6: Enable DHCP Service for Port 2.
- 7: Click **{Accept}**. A reboot of the desk is required.

Software Components

Eos Family Lighting Control Software Components

Eos Family Console Main Application	2.5.2.9.0.8
ECU	2.5.2.9.0.4
XPe (Eos)	2.2.0.9.0.3
XPe (Eos with 2400 video card)	2.3.0.9.0.5
XPe (Eos RPU)	2.2.0.9.0.3
XPe (Eos RPU with 2270 video card)	2.3.0.9.0.2
XPe (Eos RPU w BCM motherboard)	2.4.0.9.0.4
XPe (Ion)	2.2.0.9.0.3
XPe (Ion with BCM motherboard)	2.3.0.9.0.3
XPe (Ion RPU)	2.2.0.9.0.3
XPe (Ion RPU with 2270 video card)	2.3.0.9.0.2
XPe (Ion RPU w BCM motherboard)	2.4.0.9.0.2
XPe (Element)	2.2.0.9.0.3
XPe (RVI)	2.5.0.9.0.1
XPe (RVI with 2270 video card)	2.5.0.9.0.1
XPe (RVI w BCM motherboard)	2.5.0.9.0.1
Wes7 (Gio)	3.0.0.9.0.20
Wes7 (Gio UCB)	4.0.0.9.0.3
Wes7 (Gio @ 5)	1.0.0.9.0.1
Wes7 (Eos Ti)	1.0.0.9.0.10
Wes7 (Eos Ti UCB)	2.0.0.9.0.3
Wes7 (RPU3)	3.0.0.9.0.20
Wes7 (RPU3_Q87)	4.0.0.9.0.1
RPU3_Q87 BIOS	R1.1 (V00XTM11)
Wes7 (RVI3)	3.0.0.9.0.20
Wes7 (RVI3_Q87)	4.0.0.9.0.1
RVI3_Q87 BIOS	R1.1 (V00XTM11)
Wes7 (Aaeon Element)	7.0.0.9.0.2
Wes7 (Aaeon Ion)	7.0.0.9.0.1
Wes7 (Aaeon Ion RPU)	7.0.0.9.0.1
Wes7 (Aaeon RVI)	7.0.0.9.0.1
Wes7 (Puck)	1.0.0.9.0.1
Wes7 (Puck2)	2.0.0.9.0.1
ACN Libraries	1.4.3.9.0.2
ETCNet2	4.0.19.9.0.1
Network Common	1.3.3.9.0.1
Network IPCFG	1.3.3.9.0.1
Carallon Library	2.5.1.9.0.6